



# USER GUIDE

Gateway Notebook





# Contents

---

<b>Chapter 1: About this reference</b> .....	<b>1</b>
About this guide .....	2
Accessing the online User Guide .....	2
Gateway contact information .....	2
Gateway model and serial number .....	2
Microsoft Certificate of Authenticity .....	3
For more information .....	3
<b>Chapter 2: Checking Out Your Gateway Notebook</b> .....	<b>5</b>
Identifying features .....	6
Front .....	6
Left .....	7
Right .....	8
Back .....	8
Bottom .....	9
Keyboard area .....	10
Connecting the AC adapter .....	11
Protecting from power source problems .....	12
Connecting the dial-up modem .....	12
Connecting to a cable or DSL modem or to an Ethernet network .....	13
Starting your notebook .....	14
Waking up your notebook .....	14
Turning off your notebook .....	14
Restarting (rebooting) your notebook .....	15
Using the status indicators .....	16
Using the keyboard .....	17
Key types .....	17
System key combinations .....	18
Using the EZ Pad touchpad .....	20
Adjusting the volume .....	21
Turning your wireless radio on or off .....	22
Using the DVD drive .....	23
Identifying drive types .....	23
Inserting a CD or DVD .....	24
Using the memory card reader .....	25
Memory card types .....	25
Inserting a memory card .....	25
Using a memory card .....	25
Removing a memory card .....	25
Adding and removing a PC Card .....	26
Changing batteries .....	27
Recalibrating the battery .....	28
Ordering accessories .....	29

**Chapter 3: Maintaining and Upgrading Your Notebook .....31**

- Preventing static electricity discharge .....32
- Adding or replacing memory .....32
- Replacing the DVD drive .....34
- Replacing the hard drive kit .....37
- Replacing the keyboard .....41
  - Removing the keyboard .....41
  - Installing the keyboard .....44

**Appendix A: Safety, Regulatory, and Legal Information ..... 45**

**Index ..... 57**

# CHAPTER 1

## About this reference

- [About this guide](#)
- [Accessing the online User Guide](#)
- [Gateway contact information](#)
- [Microsoft Certificate of Authenticity](#)
- [For more information](#)

## About this guide

This guide includes information and maintenance instructions that are specific to your model of Gateway notebook. For all other notebook information, see your online *User Guide*.

## Accessing the online User Guide

In addition to this guide, the online *User Guide* has been included on your hard drive. The *User Guide* is an in-depth, easy-to-read manual that includes information on the following topics:

- Help and technical support
- Using and customizing Windows and other software
- Controlling audio and video settings
- Using the Internet
- Protecting your files
- Playing and recording media
- Networking
- Maintenance and troubleshooting



**To access the online *User Guide*:**

- Click **Start, All Programs**, then click **Gateway Documentation**.



## Gateway contact information

### Gateway model and serial number



**Important**

*The label shown in this section is for informational purposes only. Label information varies by model, features ordered, and location.*

The label on the bottom of your notebook contains information that identifies your notebook model and its features. Gateway Customer Care will need this information if you call for assistance.



# Microsoft Certificate of Authenticity

The Microsoft Certificate of Authenticity label found on the bottom of your notebook includes the product key code for your operating system.



## For more information

For more information about your notebook, visit Gateway's *Support* page at [support.gateway.com](http://support.gateway.com) or the Web address shown on your notebook's label. The *Support* page also has links to additional Gateway documentation and detailed specifications.




# CHAPTER 2




## Checking Out Your Gateway Notebook

- Identifying features
- Connecting the AC adapter
- Connecting the dial-up modem
- Connecting to a cable or DSL modem or to an Ethernet network
- Starting your notebook
- Turning off your notebook
- Restarting (rebooting) your notebook
- Using the status indicators
- Using the keyboard
- Using the EZ Pad touchpad
- Adjusting the volume
- Turning your wireless radio on or off
- Using the DVD drive
- Using the memory card reader
- Adding and removing a PC Card
- Changing batteries
- Recalibrating the battery
- Ordering accessories


# Identifying features





## Front



Component	Icon	Description
Volume control		<ul style="list-style-type: none"> <li>Press the button to the right to increase the volume.</li> <li>Press the button to the left to decrease the volume.</li> <li>Press the button in to mute the volume.</li> </ul>
Microphone jack		Plug a microphone into this jack.
Headphone jack		Plug amplified speakers or headphones into this jack. The built-in speakers are turned off when speakers or headphones are plugged into this jack.
Memory card reader		Insert a memory card from a digital camera, MP3 player, PDA, or cellular telephone into the memory card reader. For more information, see <a href="#">"Using the memory card reader" on page 25</a> . The memory card reader supports Memory Stick <sup>®</sup> , Memory Stick Pro <sup>®</sup> , MultiMediaCard <sup>™</sup> , and Secure Digital <sup>™</sup> cards.
LCD panel release latch		Slide to open the LCD panel.

## Left




Component	Icon	Description
Modem jack		Plug a modem cable into this jack. For more information, see <a href="#">“Connecting the dial-up modem”</a> on page 12.
USB ports		Plug USB devices (such as a diskette drive, flash drive, printer, scanner, camera, keyboard, or mouse) into these ports.
Ventilation fan		Helps cool internal components. <b>Warning:</b> Do not work for long periods with the notebook resting on your lap. If the air vents are blocked, the notebook may become hot enough to harm your skin. <b>Caution:</b> Do not block or insert objects into these slots. If these slots are blocked, your notebook may overheat resulting in unexpected shutdown or permanent damage to the notebook. <b>Caution:</b> Provide adequate space around your notebook so air vents are not obstructed. Do not use the notebook on a bed, sofa, rug, or other similar surface.
Monitor port		Plug an analog VGA monitor or projector into this port. For more information, see <a href="#">“Viewing the display on a projector or monitor”</a> in the online <i>User Guide</i> .
PC Card slot		Insert one Type II PC Card into this slot. For more information, see <a href="#">“Adding and removing a PC Card”</a> on page 26.

## Right



Component	Icon	Description
IEEE 1394 port	1394	Plug an IEEE 1394 (also known as Firewire® or i.Link®) device (such as a digital camcorder) into this 4-pin IEEE 1394 port.
DVD drive		Insert CDs or DVDs into this drive. For more information, see <a href="#">“Using the DVD drive” on page 23</a> . To determine the type of drive in the notebook, examine the drive tray’s plastic cover and compare the logo to those listed in <a href="#">“Identifying drive types” on page 23</a> .
Power connector		Plug the AC adapter cable into this connector.





## Back



Component	Icon	Description
Kensington™ lock slot		Secure your notebook to an object by connecting a Kensington cable lock to this slot.
Power/ battery charge indicator		<ul style="list-style-type: none"> <li>▪ LED solid blue - notebook is on, and if the notebook is connected to AC power, the battery is fully charged.</li> <li>▪ LED blinking blue - notebook is in Standby mode.</li> <li>▪ LED solid purple - battery is charging.</li> <li>▪ LED blinking purple - battery is charging and notebook is in Standby mode.</li> <li>▪ LED blinking red - battery charge is very low and has insufficient power to turn on the notebook.</li> <li>▪ LED off - notebook is off.</li> </ul>
Ethernet jack		Plug an Ethernet network cable into this jack. Plug the other end of the cable into a cable modem, DSL modem, or an Ethernet network jack. For more information, see <a href="#">“Connecting to a cable or DSL modem or to an Ethernet network” on page 13</a> .


## Bottom



Component	Icon	Description
Battery		Provides power when the notebook is not plugged into AC power.
Battery lock		Slide to unlock the battery. For more information, see <a href="#">“Changing batteries” on page 27</a> .
Memory bay		Install a memory module into this bay. For more information, see <a href="#">“Adding or replacing memory” on page 32</a> .
Hard drive bay		The hard drive is located in this bay. For more information, see <a href="#">“Replacing the hard drive kit” on page 37</a> .
System label		Includes the product model number. For more information, see <a href="#">“Gateway model and serial number” on page 2</a> .
Battery latch		Slide to release the battery. For more information, see <a href="#">“Changing batteries” on page 27</a> .

## Keyboard area



Component	Icon	Description
Power button		Press to turn the power on or off. You can also configure the power button for Standby/Resume mode. For more information on configuring the power button mode, see "Changing Power-Saving Settings" in the online <i>User Guide</i> .
Keyboard		Provides all the features of a full-sized, computer keyboard. For more information, see "Using the keyboard" on page 17.
Touchpad		Provides all the functionality of a mouse. For more information, see "Using the EZ Pad touchpad" on page 20.
Status indicators		Inform you when a drive is in use or when a button has been pressed that affects how the keyboard is used. For more information, see "Using the status indicators" on page 16.

# Connecting the AC adapter

## Warning

Do not attempt to disassemble the AC adapter. The AC adapter has no user-replaceable or user-serviceable parts inside. The AC adapter has dangerous voltages that can cause serious injury or death. Contact Gateway about returning defective AC adapters.

## Caution

Make sure that you use the AC adapter that came with your notebook or one of the same type purchased from Gateway. Replace the power cord if it becomes damaged. The replacement cord must be of the same type and voltage rating as the original cord or your notebook may be damaged.

## Important

If the battery charge indicator does not turn blue after three hours, contact Gateway Customer Care at [support.gateway.com](http://support.gateway.com).

## Important

If the battery is not fully charged before you use your notebook on battery power for the first time, the battery life may be much shorter than you expect. If the battery life seems short even after being charged for three hours, the battery may need to be recalibrated. For information on recalibrating the battery, see "Recalibrating the battery" on page 28.

You can run your notebook using an AC adapter or your notebook's battery. The battery was shipped to you partially charged. You should use the AC adapter right away to fully charge the battery. Allow three hours for the battery to fully charge.

## To connect the AC adapter:

- 1 Connect the power cord to the AC adapter.



- 2 Connect the AC adapter to your notebook's power connector.



- 3 Plug the power cord into a wall outlet. The power/battery charge indicator turns on (see "Back" on page 8 for the location of the power/battery charge indicator). If the power/battery charge battery charge indicator does not turn on, complete the following steps until it turns on:
  - a Unplug the adapter from your notebook, then plug it back in.
  - b Press **FN+F1** to toggle the status lights on and off.
- 4 When you finish using your notebook for the first time, turn off your notebook and leave your notebook connected to AC power until the battery charge indicator turns blue.



## Protecting from power source problems

### **Warning**

High voltages can enter your notebook through both the power cord and the modem connection. To protect your notebook and avoid electrical shock, use a surge protector. If you have a telephone modem, use a surge protector that has a modem jack. If you have a cable modem, use a surge protector that has an antenna/cable TV jack. During an electrical storm, unplug both the surge protector and the modem.

During a power surge, the voltage level of electricity coming into your notebook can increase to levels far above normal levels and cause data loss or system damage. Protect your notebook and peripheral devices by connecting them to a *surge protector*, which absorbs voltage surges and prevents them from reaching your notebook.


## Connecting the dial-up modem

### **Warning**

To reduce the risk of fire, use only No. 26 AWG or larger telecommunications line cord.

Your notebook has a built-in 56K modem that you can use to connect to a standard telephone line.

### **To connect the modem:**

- 1 Insert one end of the modem cable into the modem jack  on the left side of your notebook.




- 2 Insert the other end of the modem cable into a telephone wall jack. The modem will not work with digital or PBX telephone lines.
- 3 Start your notebook, then start your communications program.



# Connecting to a cable or DSL modem or to an Ethernet network

Your notebook has a network jack that you can use to connect to a cable or DSL modem or to an Ethernet network.

**▶ To connect to a cable or DSL modem or to an Ethernet network:**

- 1 Insert one end of the network cable into the network jack  on the back of your notebook.



- 2 Insert the other end of the network cable into a cable modem, DSL modem, or Ethernet network jack.



## Starting your notebook

### Warning

Do not work for long periods with the notebook resting on your lap. If the air vents are blocked, the notebook may become hot enough to harm your skin.

### Caution

Provide adequate space around your notebook so air vents are not obstructed. Do not use the notebook on a bed, sofa, rug, or other similar surface.

### Tips & Tricks

For more information about changing the power button mode, see "Changing Power-Saving Settings" in the online User Guide.

### To start your notebook:

- 1 Slide the latch on the front of your notebook, then lift the LCD panel.
- 2 Press the power button located above the keyboard.



- 3 If you are starting your notebook for the first time, follow the on-screen instructions to set up your notebook.



## Waking up your notebook

### Tips & Tricks

For more information about Standby mode, see "Changing power modes" in the online User Guide.

When you have not used your notebook for several minutes or if you close the LCD panel without turning off your notebook, it may enter a power-saving mode called *Standby*. While in Standby, the power indicator flashes. If your notebook is in Standby mode, press the power button to "wake" it up.

## Turning off your notebook

### Important

If for some reason you cannot use the Turn Off Computer option in Windows to turn off your notebook, press and hold the power button for about five seconds, then release it.

### To turn off your notebook:

- 1 Click **Start**, then click **Turn Off Computer**. The *Turn Off Computer* dialog box opens.
- 2 Click **Turn Off**. Windows shuts down and turns off your notebook.



# Restarting (rebooting) your notebook



## Important

If your notebook does not turn off immediately, complete the following steps until the notebook turns off:

1. Press and hold the power button for about five seconds, then release it.
2. Unplug the power cord and remove the battery for more than 10 seconds.

If your notebook does not respond to keyboard, touchpad, or mouse input, you may have to close programs that are not responding. If closing unresponsive programs does not restore your notebook to normal operation, you may have to restart (reboot) your notebook.



### To close unresponsive programs and restart your notebook:

- 1 Press **CTRL+ALT+DEL**. The *Windows Security* dialog box opens.
- 2 Click **Task Manager**. The *Windows Task Manager* dialog box opens.
- 3 Click the program that is not responding.
- 4 Click **End Task**.
- 5 Click **X** in the top-right corner of the *Windows Task Manager* dialog box.
- 6 If your notebook does not respond, turn it off, wait ten seconds, then turn it on again.

As a part of the regular startup process, a program to check the disk status runs automatically. When the checks are finished, Windows starts.









## Using the status indicators

### Important

If none of the indicators are on, you may need to press **FN+F1** to toggle the status indicators on and off.

Status indicators inform you when a drive is being used or when a button has been pressed that affects how the keyboard is used. The status indicators are located below the touchpad.



Indicator	Icon	Description
AC power		<ul style="list-style-type: none"> <li>LED on - AC power is connected.</li> <li>LED off - AC power is not connected.</li> </ul>
Wireless network (optional)		<ul style="list-style-type: none"> <li>LED on - Wireless network is turned on.</li> <li>LED off - Wireless network is turned off.</li> </ul>
Caps lock		<ul style="list-style-type: none"> <li>LED on - Caps lock is turned on.</li> <li>LED off - Caps lock is turned off.</li> </ul>
Num lock		<ul style="list-style-type: none"> <li>LED on - Numeric keypad is turned on.</li> <li>LED off - Numeric keypad is turned off.</li> </ul>
Drive		<ul style="list-style-type: none"> <li>LED blinking - The hard drive or DVD drive is in use.</li> <li>LED off - The hard drive or DVD drive is not in use.</li> </ul>

# Using the keyboard



## Tips & Tricks

You can attach an external keyboard to the notebook using a USB port. You do not need to shut down the notebook to connect a USB keyboard.



Your notebook features a full-size keyboard that functions the same as a desktop computer keyboard. Many of the keys have been assigned alternate functions, including shortcut keys for Windows, function keys for specific system operations, and the Num Lock keys for the numeric keypad.



## Key types








The keyboard has several different types of keys. Some keys perform specific actions when pressed alone and other actions when pressed in combination with another key.

Key type	Icon	Description
Function keys		Press these keys labeled <b>F1</b> to <b>F12</b> to perform actions in programs. For example, pressing <b>F1</b> may open help. Each program uses different function keys for different purposes. See the program documentation to find out more about the function key actions.
System keys		Press these colored keys in combination with the <b>FN</b> key to perform specific actions. For more information, see " <a href="#">System key combinations</a> " on page 18.
Navigation keys		Press these keys to move the cursor to the beginning of a line, to the end of a line, up the page, down the page, to the beginning of a document, or to the end of a document.
Arrow keys		Press these keys to move the cursor up, down, right, or left.
Application key		Press this key for quick access to shortcut menus and help assistants in Windows.

Key type	Icon	Description
Windows key		Press this key to open the Windows <b>Start</b> menu. This key can also be used in combination with other keys to open utilities like <b>F</b> (Search utility), <b>R</b> (Run utility), and <b>E</b> (Explorer utility).
<b>FN</b> key		Press the <b>FN</b> key in combination with a colored system key to perform a specific action.
Numeric keypad		Use these keys to type numbers when the numeric keypad is turned on. Press <b>FN</b> +  to turn on the numeric keypad.

## System key combinations

When you press the **FN** key and a system key at the same time, your notebook performs the action identified by the text or icon on the key.

Press and hold <b>FN</b> , then press this system key...	To...
	Toggle the status indicators on or off. For more information, see <a href="#">"Using the status indicators" on page 16</a> .
	Turn the optional wireless network on or off. For more information, see <a href="#">"Wireless Networking"</a> in the online <i>User Guide</i> . <b>Warning:</b> Radio frequency wireless communication can interfere with equipment on commercial aircraft. Current aviation regulations require wireless devices to be turned off while traveling in an airplane. 802.11G (also known as wireless Ethernet or Wifi) communication devices are examples of devices that provide wireless communication.
	Enter Standby mode. Press the power button to leave Standby mode. For more information, see <a href="#">"Changing Power-Saving Settings"</a> in the online <i>User Guide</i> .
	Toggle the notebook display in the following order: <ul style="list-style-type: none"> <li>▪ The LCD</li> <li>▪ An external monitor or projector (a monitor or projector must be plugged into the monitor port on your notebook)</li> <li>▪ Both displays at the same time</li> </ul> For more information, see <a href="#">"Viewing the display on a projector or monitor"</a> in the <i>User Guide</i> .
	Decrease the LCD panel brightness.
	Increase the LCD panel brightness.
	Play or Pause the CD or DVD.

**Press and hold FN, then  
press this system key...**

**To...**



Stop playing the CD or DVD.



Skip back one CD song or DVD track.



Skip ahead one CD song or DVD track.



Turn on Num Lock so you can use the numeric keypad. Press this key combination again to turn off Num Lock. The Num Lock status indicator appears when this function is turned on.

# Using the EZ Pad touchpad


 **Tips & Tricks**

For instructions on how to adjust the double-click speed, pointer speed, right-hand or left-hand configuration, and other touchpad settings, see "Changing the mouse or touchpad settings" in the online User Guide.

 **Tips & Tricks**

You received your notebook with the EZ Pad touchpad set to only accept clicking by using the touchpad buttons. You can change this feature to allow tapping on the touchpad to simulate clicking the left button. For more information, see "Changing the mouse or touchpad settings" in the online User Guide.


The EZ Pad™ consists of a touchpad, two buttons, and a scroll zone.







When you move your finger on the touchpad, the *pointer* (arrow) on the screen moves in the same direction. You can use the scroll zone to scroll through documents. Use of the scroll zone may vary from program to program.



You can use the EZ-Pad *left* and *right* buttons below the touchpad to select objects.

To...	Do this...
Move the pointer on the screen.	 <p>Move your finger around on the touchpad. If you run out of space and need to move the pointer farther, lift your finger, move it to the middle of the touchpad, then continue moving your finger.</p>

To...	Do this...	
Select an object on the screen.		Position the pointer over the object. Quickly press and release the left button once. This action is called <i>clicking</i> .
Start a program or open a file or folder.		Position the pointer over the object. Press the left button twice in rapid succession. This action is called <i>double-clicking</i> .
Access a shortcut menu or find more information about an object on the screen.		Position the pointer over the object. Quickly press and release the right button once. This action is called <i>right-clicking</i> .
Move an object on the screen.		Position the pointer over the object. Press the left button and hold it down, then use the touchpad to move (drag) the object to the appropriate part of the screen. Release the button to drop the object where you want it.

## Adjusting the volume



### Tips & Tricks

For instructions on how to adjust the volume in Windows, see "Adjusting the Volume" in the online User Guide.

You can use the volume control to adjust the overall volume of your notebook.



#### To adjust the overall volume level using hardware controls:

- If you are using external speakers, turn the knob on the front of the speakers.

-OR-

Press the volume control on the notebook. For more information, see "Front" on page 6.



# Turning your wireless radio on or off

## **Warning**

Radio frequency wireless communication can interfere with equipment on commercial aircraft. Current aviation regulations require wireless devices to be turned off while traveling in an airplane. IEEE 802.11a, IEEE 802.11b, and IEEE 802.11g communication devices are examples of devices that provide wireless communication.

## **Warning**

In environments where the risk of interference to other devices or services is harmful or perceived as harmful, the option to use a wireless device may be restricted or eliminated. Airports, hospitals, and oxygen or flammable gas laden atmospheres are limited examples where use of wireless devices may be restricted or eliminated. When in environments where you are uncertain of the sanction to use wireless devices, ask the applicable authority for authorization prior to using or turning on the wireless device.

## **Tips & Tricks**

For more information about using your notebook on a wireless network, see "Wireless Networking" in the online User Guide.

Your Gateway notebook may have a factory-installed wireless networking mini-PCI card.



### **To turn the wireless radio on or off:**

- Press **FN + F2**. The wireless status indicator turns on or off. For the location of the wireless status indicator, see ["Using the status indicators" on page 16](#).






# Using the DVD drive


You can use your notebook to enjoy a wide variety of multimedia features.

## Identifying drive types

Your Gateway notebook may contain one of the following drive types. Look on the front of the drive for one or more of the following logos:

If your drive has this logo...	This is your drive type...	Use your drive for...
	<b>DVD drive</b>	Installing programs, playing audio CDs, playing DVDs, and accessing data. You cannot use this drive to create CDs or DVDs.
	<b>Combination DVD/CD-RW drive</b>	Installing programs, playing audio CDs, playing DVDs, accessing data, and recording music and data to recordable CDs. You cannot use this drive to create DVDs.
	<b>Multi-format double layer DVD±RW/CD-RW drive</b>	Installing programs, playing audio CDs, playing DVDs, accessing data, recording music and data to CD-R or CD-RW discs, and recording video and data to DVD-R, DVD+R, DVD-RW, DVD+RW, or double layer DVD+R discs. <b>Note:</b> To use the double layer capability of the double layer recordable DVD drive, the blank DVDs you purchase must state Double Layer, Dual Layer, or DL. Using other types of blank media will result in less capacity.

## Inserting a CD or DVD



### To insert a CD or DVD:

- 1** Press the eject button on the DVD drive. After the tray opens slightly, pull the disc tray completely open.
- 2** Place the disc in the tray with the label facing up, then press down carefully on the disc until it snaps into place.
- 3** Push the tray in until it is closed.

#### Important

*When you place a single-sided disc in the tray, make sure that the label side is facing up. If the disc has two playable sides, place the disc so the name of the side you want to play is facing up.*

# Using the memory card reader

You can use memory cards to transfer pictures from a digital camera to your notebook. You can also use the memory card reader to transfer data between your notebook and a device that uses memory cards, such as a PDA, MP3 player, or cellular telephone.

## Memory card types

The memory card reader supports Memory Stick®, Memory Stick Pro®, MultiMediaCard™, and Secure Digital™.

## Inserting a memory card

### To insert a memory card:

- Insert the memory card into the memory card slot with the label facing up and the arrow on the label pointing towards the notebook.




## Using a memory card

### To access a file on a memory card:

- 1 Click **Start**, then click **My Computer**.
- 2 Double-click the drive letter (for example, the E: drive), then double-click the file name.



## Removing a memory card

 **Important**  
Do not use the remove hardware  icon in the taskbar to remove the memory card. If you use the remove hardware icon, your notebook may not recognize your memory card reader until you restart your notebook.

### To remove a memory card:

- 1 Push the memory card into the notebook. The memory card pops out slightly.
- 2 Pull the memory card out of the notebook.



## Adding and removing a PC Card


Your notebook has a PC Card slot (also known as a PCMCIA card slot). This slot accepts one Type II card. You do not need to restart your notebook when changing most cards because your notebook supports *hot-swapping*. Hot-swapping means that you can insert a PC Card while your notebook is running. If your PC Card does not work after hot-swapping, see the PC Card manufacturer's documentation for further information.

### ▶ To insert a PC Card:

- Push the card firmly into the PC Card slot, label-side up, until the outer edge of the card is flush with the side of your notebook.



### ▶ To remove a PC Card:

- 1 Click the remove hardware  icon in the taskbar, the PC Card name, then click **Stop**.

-OR-

Turn off your notebook.

- 2 Release the eject button by pressing the PC Card eject button once.
- 3 Eject the PC Card by pressing the eject button again.



### Important

If the remove hardware icon does not appear on the taskbar, click the show hidden icons  button.

# Changing batteries

## Warning

*Danger of explosion if battery is incorrectly replaced. Replace only with a battery specifically manufactured for your Gateway notebook. Discard used batteries according to local hazardous material regulations.*

*The battery used in this device may present a fire or chemical burn hazard if mishandled. Do not disassemble, heat above 212°F (100°C), or incinerate. Dispose of used battery promptly. Keep away from children.*

If your notebook is connected to AC power, you can change the battery while the notebook is turned on. If your notebook is not plugged into an AC outlet, you must turn the notebook off while changing the battery.

## To change the battery:

- 1 If your notebook is on and is connected to AC power, go to [Step 2](#).

-OR-

If your notebook is on and is not plugged into an AC outlet, save your work and turn off your notebook.

- 2 Close the LCD panel.
- 3 Turn your notebook over so the bottom is facing up.
- 4 Slide the battery lock to the unlocked position, then slide the battery release latch.



- 5 Slide the battery out of the notebook.



- 6 Slide a recharged battery into the notebook until it snaps into place.



- 7 Slide the battery lock to the locked position.

- 8 Turn your notebook over.
- 9 Open the LCD panel.



## Recalibrating the battery

### **Important**

*Do not interrupt the battery recalibration process. If recalibration is interrupted, you must start the process over again.*

If your notebook unexpectedly goes into Standby mode while you are using it but the battery charge is not low, you may need to recalibrate your battery. You should also recalibrate the battery periodically to maintain the accuracy of the battery gauge.

### **To recalibrate the battery:**

- 1 Close all open files and programs.
- 2 Connect your notebook to AC power and let the battery charge completely.
- 3 Disconnect the AC power and restart your notebook.
- 4 Completely discharge the battery by doing the following:
  - a From the desktop, right-click on the power icon, then select **Adjust Power Properties**.
  - b Click the **Power Schemes** tab.
  - c Click the arrow button to open the **Power Schemes** list, then click **Always On**.
  - d Click the **Alarms** tab.
  - e Click to clear the **Low battery alarm** and **Critical battery alarm** check boxes. Let the battery drain until your notebook automatically turns off.
- 5 After the battery is completely drained, reconnect your notebook to AC power.
- 6 Charge the battery completely until the battery status indicator turns blue.
- 7 When you are ready to use your notebook again, do the following:
  - a From the desktop, right-click the power icon, then select **Adjust Power Properties**.
  - b Click the **Power Schemes** tab.
  - c Click the arrow button to open the **Power Schemes** list, then click **Portable/Laptop**.
  - d Click the **Alarms** tab.
  - e Click to select the **Low battery alarm** and **Critical battery alarm** check boxes.



# Ordering accessories

To order accessories, visit the Accessory Store at [accessories.gateway.com](http://accessories.gateway.com).

## Batteries

If you run your notebook on battery power for extended periods, you may want to buy an additional battery so you can swap batteries when necessary. See ["Changing batteries" on page 27](#) for more information about using an additional battery.

## Carrying cases

Gateway has large-capacity carrying cases if you need additional space for accessories or supplies.

## Memory

Large programs, such as multimedia games or graphics programs, use a lot of memory. If your programs are running more slowly than you think they should, try adding more memory. See ["Adding or replacing memory" on page 32](#) for more information.

## Printers

You can attach almost any type of printer to your notebook. The most common types are inkjet and laser printers, which print in color or black and white.

Inkjet printers and cartridges are relatively inexpensive, but they are slower than laser printers. Using an inkjet color printer, you can print pictures, banners, and greeting cards, as well as documents.

Laser printers and cartridges are more expensive, but they print much faster than inkjet printers. Laser printers are better than inkjet printers when you are printing large documents.

## USB flash drive

Use a USB flash drive for storing files or transferring files to another computer.



# CHAPTER 3

## Maintaining and Upgrading Your Notebook

- Preventing static electricity discharge
- Adding or replacing memory
- Replacing the DVD drive
- Replacing the hard drive kit
- Replacing the keyboard

## Preventing static electricity discharge

### Warning

To avoid exposure to dangerous electrical voltages and moving parts, turn off your notebook and unplug the power cord, modem cable, and network cable before opening the case.

### Warning

To prevent risk of electric shock, do not insert any object into the vent holes of the notebook.

### Important

Before installing or replacing components, you should read and understand the information in this section.

The components inside your notebook are extremely sensitive to static electricity, also known as *electrostatic discharge* (ESD).

Before installing or replacing components, follow these guidelines:

- Avoid static-causing surfaces such as carpeted floors, plastic, and packing foam.
- Remove components from their antistatic bags only when you are ready to use them. Do not lay components on the outside of antistatic bags because only the inside of the bags provide electrostatic protection.
- Always hold components by their edges. Avoid touching the edge connectors. Never slide components over any surface.
- Wear a grounding wrist strap (available at most electronics stores) and attach it to a bare metal part of your workbench or other grounded connection.
- Touch a bare metal surface on your workbench or other grounded object.

## Adding or replacing memory

### Important

Use only memory modules designed for your Gateway notebook.

### Tools Required

You need a small Phillips screwdriver to replace memory.

Your notebook uses memory modules called SO-DIMMs (Small Outline Dual Inline Memory Modules). The modules are available in various capacities and any module can be placed in any slot.




### To add or replace memory modules:

- 1 Follow the guidelines under “Preventing static electricity discharge” on page 32.
- 2 Turn off your notebook.
- 3 Disconnect the AC adapter, modem cable, and network cable.


- 4 Disconnect all peripheral devices and remove any PC cards.
- 5 Turn your notebook over so the bottom is facing up, then remove the battery. For more information, see ["Changing batteries" on page 27](#).
- 6 Remove the memory bay cover screw.



- 7 Slide the memory bay cover, then remove it.
- 8 If you are removing a module, gently press outward on the clip at each end of the memory module until the module tilts upward.



- 9 Pull the memory module out of the slot.



- 10 Hold the new or replacement module at a 30-degree angle and press it into the empty memory slot. This module is keyed so it can only be inserted in one direction. If the module does not fit, make sure that the notch in the module lines up with the tab in the memory bay.
- 11 Replace the memory bay cover, then replace the cover screw.
- 12 Insert the battery, then turn your notebook over.
- 13 Connect the power adapter, modem cable, and network cable, then turn on your notebook.



## Replacing the DVD drive

### Important

Replace the DVD drive only with a similar drive provided by Gateway.

### Tools Required

You need a small Phillips screwdriver to replace the DVD drive.

If your DVD drive becomes damaged, you can replace it with a similar drive obtained from Gateway.

### To replace the DVD drive:

- 1 Make sure that the DVD drive is empty.
- 2 Follow the guidelines under [“Preventing static electricity discharge”](#) on page 32.
- 3 Turn off your notebook.
- 4 Disconnect the AC adapter, modem cable, and network cable.
- 5 Disconnect all peripheral devices and remove any PC Cards.
- 6 Turn your notebook over so the bottom is facing up, then remove the battery. For more information, see [“Changing batteries”](#) on page 27.

7 Remove the two DVD drive screws.



8 Turn the notebook over so the top is facing up.

9 Insert a straightened paper clip into the DVD drive's manual eject hole, push in the paper clip to eject the drive tray, then pull the drive tray open.



- 10 Slide the drive out of the notebook.



- 11 Insert the new drive into the notebook.
- 12 Turn the notebook over so the bottom is facing up.
- 13 Replace the two screws.
- 14 Insert the battery, then turn your notebook over.
- 15 Connect the power adapter, modem cable, and network cable, then turn on your notebook.



# Replacing the hard drive kit



## Tools Required

You need a small Phillips screwdriver to replace the hard drive kit.

If you would like more hard drive capacity, you can replace your original drive with a higher-capacity drive.



### To replace the hard drive kit:


- 1 Create a *Drivers and Applications Recovery* disc. For more information, see “Creating Drivers and Applications Recovery discs” in the online *User Guide*.
- 2 Print the “Recovering Your System” chapter from the online *User Guide* for use in [Step 22](#).
- 3 Back up any data you want to transfer to the new hard drive. For more information, see “Backing up files” in the online *User Guide*.
- 4 Follow the guidelines under “[Preventing static electricity discharge](#)” on [page 32](#).
- 5 Turn off your notebook.
- 6 Disconnect the AC adapter, modem cable, and network cable.
- 7 Disconnect all peripheral devices and remove any PC cards.
- 8 Turn your notebook over so the bottom is facing up, then remove the battery. For more information, see “[Changing batteries](#)” on [page 27](#).

- 9 Remove the hard drive bay cover screw.



- 10 Slide the hard drive bay cover, then remove it.

- 11 Remove the two screws securing the hard drive kit to the notebook.



- 12** Slide the old hard drive kit away from the hard drive connector, then lift the hard drive kit out of your notebook.



- 13** If your new hard drive already includes the hard drive bracket, go to [Step 18](#).

-OR-

If you need to move the hard drive bracket from your old hard drive to your new hard drive, go to [Step 14](#).

- 14** Remove the four screws that secure the hard drive to the hard drive kit bracket.



- 15** Remove the old drive from the bracket.



- 16** Insert the new drive into the bracket so the screw holes line up.
- 17** Replace the screws that secure the bracket to the drive.
- 18** Slide the new hard drive kit into your notebook, then replace the screws that secure the hard drive kit to the notebook.
- 19** Replace the hard drive bay cover, then replace the cover screw.
- 20** Insert the battery, then turn your notebook over.
- 21** Connect the power adapter, modem cable, and network cable, then turn on your notebook.
- 22** For instructions on installing Windows, your drivers, and your applications, see the *Recovering Your System* chapter you printed in [Step 2](#).



# Replacing the keyboard

**Important**

Replace the keyboard only with a similar keyboard provided by Gateway.

**Tools Required**


You need a small Phillips and a small flat-blade screwdriver to replace the keyboard.

If your keyboard becomes damaged, you can replace it with a similar keyboard obtained from Gateway.

## Removing the keyboard

**To remove the keyboard:**

- 1 Follow the guidelines under [“Preventing static electricity discharge” on page 32.](#)
- 2 Turn off your notebook.
- 3 Disconnect the AC adapter, modem cable, and network cable.
- 4 Disconnect all peripheral devices and remove any PC Cards.
- 5 Turn your notebook over so the bottom is facing up, then remove the battery. For more information, see [“Changing batteries” on page 27.](#)
- 6 Remove the three keyboard cover screws.



- 7 Turn the notebook over so the top is facing up.
- 8 Open the LCD panel to the normal viewing position.

 **Important**

Inserting a piece of cloth between the screwdriver and keyboard will help prevent damage to your notebook.

- 9 Insert the small flat-blade screwdriver or non-marring tool under the keyboard cover near the power button and gently pry it up.




- 10 Pull the cover off the notebook. You will hear small snapping sounds as the cover comes away from the notebook. Be careful not to break off the cable located under the power button.




- 11 Lift the back edge of the keyboard slightly, then carefully push it toward the LCD panel to release the keyboard retaining tabs.



- 12 Carefully rotate the keyboard toward you so it lies **keys-down** on top of your notebook. Be careful not to damage the LCD panel.



- 13 Slide the brown keyboard connector clip to the front of the notebook, then remove the keyboard cable. Be careful not to touch or damage any other components.



## Installing the keyboard



### Important

The keyboard cable is correctly oriented if it is not twisted.

### To install the keyboard:

- 1 Place the new keyboard **keys-down** on your notebook with the space bar away from you.
- 2 Make sure the brown keyboard connector clip is fully moved toward the front of the notebook, insert the keyboard cable into the keyboard connector, then slide the brown keyboard connector clip back to lock the keyboard connector in place.
- 3 Rotate the keyboard toward the LCD panel until the keyboard is almost face-up.
- 4 Insert the tabs on the front edge of the keyboard into the slot under the palm rest. You may need to press down on the keyboard keys along the front edge of the keyboard to seat the retaining tabs into their corresponding slots.



- 5 Gently press the keyboard down until it is flat all the way across. The keyboard should easily fall into place. Be careful not to damage the LCD panel.
- 6 Place the keyboard cover on the notebook, then press down on the cover in several places until it clicks in place. The cover is correctly mounted when you can run your finger along the cover and find no loose spots. The cover should be flat all the way across.
- 7 Close the LCD panel, then turn the notebook over so the bottom is facing up.
- 8 Replace the three keyboard cover screws.
- 9 Insert the battery, then turn your notebook over.
- 10 Connect the power adapter, the modem cable, and the network cable, then turn on your notebook.



### Caution

If the keyboard cover is not correctly replaced, your notebook could be damaged when you try to close the LCD panel.

# APPENDIX A

## Safety, Regulatory, and Legal Information

- [Important safety information](#)
- [Regulatory compliance statements](#)
- [Environmental information](#)
- [Notices](#)

# Important safety information

## Warning

Always follow these instructions to help guard against personal injury and damage to your Gateway system.

## Warning

Do not use Gateway products in areas classified as hazardous locations. Such areas include patient care areas of medical and dental facilities, oxygen-laden environments, or industrial facilities.

## Warning

To reduce the risk of fire, use only No. 26 AWG or larger telecommunications line cord.

Your Gateway notebook is designed and tested to meet the latest standards for safety of information technology equipment. However, to ensure safe use of this notebook, it is important that the safety instructions marked on the notebook and in the documentation are followed.

## Setting up your system

- Read and follow all instructions marked on the notebook and in the documentation before you operate your notebook. Retain all safety and operating instructions for future use.
- Do not use this notebook near water or a heat source such as a radiator.
- Set up the notebook on a stable work surface.
- The notebook should be operated only from the type of power source indicated on the rating label.
- If your notebook has a voltage selector switch, make sure that the switch is in the proper position for your area. The voltage selector switch is set at the factory to the correct voltage.
- Openings in the notebook case are provided for ventilation. Do not block or cover these openings. Make sure you provide adequate space, at least 6 inches (15 cm), around the notebook for ventilation when you set up your work area. Never insert objects of any kind into the notebook ventilation openings.
- Some notebook are equipped with a three-wire power cord to make sure that the notebook is properly grounded when in use. The plug on this cord will fit only into a grounding-type outlet. This is a safety feature. If you are unable to insert the plug into an outlet, contact an electrician to install the appropriate outlet.
- If you use an extension cord with this notebook, make sure that the total ampere rating on the products plugged into the extension cord does not exceed the extension cord ampere rating.
- If your notebook is fitted with a TV Tuner, cable, or satellite receiver card, make sure that the antenna or cable system is electrically grounded to provide some protection against voltage surges and buildup of static charges.

## Care during use

- Do not walk on the power cord or allow anything to rest on it.
- Do not spill anything on the notebook. The best way to avoid spills is to avoid eating and drinking near your notebook.
- Some notebooks have a replaceable CMOS battery on the system board. There is a danger of explosion if the CMOS battery is replaced incorrectly. Replace the battery with the same or equivalent type recommended by the manufacturer. Dispose of batteries according to the manufacturer's instructions.
- When the notebook is turned off, a small amount of electrical current still flows through the notebook. To avoid electrical shock, always unplug all power cables and modem cables from the wall outlets before cleaning the notebook.

- Unplug the notebook from the wall outlet and refer servicing to qualified personnel if:
  - The power cord or plug is damaged.
  - Liquid has been spilled into the notebook.
  - The notebook does not operate properly when the operating instructions are followed.
  - The notebook was dropped or the cabinet is damaged.
  - The notebook performance changes.

### Replacement parts and accessories

Use only replacement parts and accessories recommended by Gateway.

# Regulatory compliance statements

## Wireless guidance



### Warning

Radio frequency wireless communication can interfere with equipment on commercial aircraft. Current aviation regulations require wireless devices to be turned off while traveling in an airplane. 802.11b (also known as wireless Ethernet or Wifi) and Bluetooth communication devices are examples of devices that provide wireless communication.



### Warning

In environments where the risk of interference to other devices or services is harmful or perceived as harmful, the option to use a wireless device may be restricted or eliminated. Airports, Hospitals, and Oxygen or flammable gas laden atmospheres are limited examples where use of wireless devices may be restricted or eliminated. When in environments where you are uncertain of the sanction to use wireless devices, ask the applicable authority for authorization prior to use or turning on the wireless device.



### Warning

If your notebook came equipped with an internal embedded wireless device, do not operate the wireless device unless all covers and shields are in place and the notebook is fully assembled.



### Caution

Wireless devices are not user serviceable. Do not modify them in any way. Modification to a wireless device will void the authorization to use it. Please contact Gateway for service.



### Caution

Only use drivers approved for the country in which the device will be used. See the Gateway System Restoration Kit, or contact Gateway Customer Care for additional information.



### Important

Every country has different restrictions on the use of wireless devices. Since your notebook is equipped with a wireless device, when traveling between countries with your notebook, check with the local Radio Approval authorities prior to any move or trip for any restrictions on the use of a wireless device in the destination country.

Low power, Radio transmitting type devices (radio frequency (RF) wireless communication devices), may be present (embedded) in your notebook system. These devices may operate in the 2.4 GHz (i.e. 802.11b/g LAN & Bluetooth), 5.2 GHz (i.e. 802.11a LAN), and traditional cellular or PCS cellular bands (i.e. Cellular data modem). The following section is a general overview of considerations while operating a wireless device.

Additional limitations, cautions, and concerns for specific countries are listed in the specific country sections (or country group sections). The wireless devices in your system are only qualified for use in the countries identified by the Radio Approval Marks on the system rating label. If the country you will be using the wireless device in, is not listed, please contact your local Radio Approval agency for requirements. Wireless devices are closely regulated and use may not be allowed.

The power output of the wireless device or devices that may be embedded in your notebook is well below the RF exposure limits as known at this time. Because the wireless devices (which may be embedded into your notebook) emit less energy than is allowed in radio frequency safety standards and recommendations, Gateway believes these devices are safe for use. Regardless of the power levels, care should be taken to minimize human contact during normal operation.

Measurements have been performed to show that the RF exposure is below what is considered safe limits; however care should be taken to make sure the user or bystanders keep the transmitter away from their body when the wireless device is transmitting. The transmitting antenna installed in the top third of the lid should be used in a manner to maintain 20 cm (8 inches) from user's or bystander's bodies.

The wireless devices installed in this system are intended to be used indoors. In some areas, use of these devices outdoors is prohibited.

Some circumstances require restrictions on wireless devices. Examples of common restrictions are listed to the left.

## United States of America



### Caution

*Wireless devices are not user-serviceable. Do not modify them in any way. Modification to a wireless device will void the authorization to use it. Contact Gateway for service.*



### Caution

*The transmitting device embedded in this notebook may not be used with any antenna other than the one provided with the notebook.*



### Caution

*In order to comply with FCC requirements this transmitter must not be operated (or co-located) in conjunction with any other transmitter or antenna installed in the notebook.*

## Federal Communications Commission (FCC) Intentional emitter per FCC Part 15

Low power, Radio transmitter type devices (radio frequency (RF) wireless communication devices), operating in the 2.4 GHz band and/or 5.15 – 5.35 GHz band, may be present (embedded) in your notebook system. This section is only applicable if these devices are present. Refer to the system label to verify the presence of wireless devices.

Wireless devices that may be in your system are only qualified for use in the United States of America if an FCC ID number is on the system label.

The FCC has set a general guideline of 20 cm (8 inches) separation between the device and the body, for use of a wireless device near the body (this does not include extremities). This device should be used more than 20 cm (8 inches) from the body when wireless devices are on. The power output of the wireless device (or devices), which may be embedded in your notebook, is well below the RF exposure limits as set by the FCC.

The wireless devices installed in this system are intended to be used indoors. In some areas, use of these devices outdoors is prohibited.

Operation of this device is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of the device.

## Unintentional emitter per FCC Part 15

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio or television reception. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause interference to radio and television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna
- Increase the separation between the equipment and receiver
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced radio/TV technician for help.

**Compliance Accessories:** The accessories associated with this equipment are: shielded video cable when an external monitor is connected. These accessories are required to be used in order to ensure compliance with FCC rules.

**Caution**

Changes or modifications not expressly approved by Gateway could void the FCC compliance and negate your authority to operate the notebook.

**Caution**

Recycle or dispose of the used notebook properly according to federal, state and local laws.

**Warning****Warning****FCC declaration of conformity****Responsible party:**

Gateway Companies, Inc.  
610 Gateway Drive, North Sioux City, SD 57049  
(605) 232-2000 Fax: (605) 232-2023

**Product:**

- Gateway NX200
- Gateway MX3000 series

This device complies with Part 15 of the FCC Rules. Operation of this product is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

**California Proposition 65 Warning**

This product contains chemicals, including lead, known to the State of California to cause cancer, birth defects or reproductive harm.

**Mercury Warning**

The lamp in this display contains mercury. Do not put in trash. Recycle or dispose as hazardous waste.

**Telecommunications per Part 68 of the Code of Federal Regulations (CFR 47) (applicable to products fitted with USA modems)**

Your modem complies with Part 68 of the Code of Federal Regulations (CFR 47) rules. On the computer or modem card is a label that contains the FCC registration number and Ringer Equivalence Number (REN) for this device. If requested, this information must be provided to the telephone company.

A telephone line cord with a modular plug is required for use with this device. The modem is designed to be connected to the telephone network or premises wiring using a compatible modular jack which is Part 68-compliant. See installation instructions for details.

The Ringer Equivalence Number (REN) is used to determine the number of devices which may be connected to the telephone line. Excessive RENs on a telephone line may result in the devices not ringing in response to an incoming call. In most areas, the sum of RENs should not exceed five (5.0). To be certain of the number of devices that may be connected to a line, as determined by the total RENs, contact the local telephone company.

If this device causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. The telephone company may request that you disconnect the equipment until the problem is resolved.

The telephone company may make changes in its facilities, equipment, operations, or procedures that could affect the operation of this equipment. If this happens, the telephone company will provide advance notice in order for you to make necessary modifications to maintain uninterrupted service.

This equipment cannot be used on telephone company-provided coin service. Connection to party line service is subject to state tariffs. Contact the state public utility commission or public service commission for information.

When programming or making test calls to emergency numbers:

- Remain on the line and briefly explain to the dispatcher the reason for the call.
- Perform such activities in the off-peak hours such as early morning or late evenings.

The United States Telephone Consumer Protection Act of 1991 makes it unlawful for any person to use a computer or other electronic device to send any message via a telephone fax machine unless such message clearly contains, in a margin at the top or bottom of each transmitted page or on the first page of the transmission, the date and time it is sent, an identification of the business, other entity, or other individual sending the message, and the telephone number of the sending machine or such business, other entity, or individual. Refer to your fax communication software documentation for details on how to comply with the fax-branding requirement.

## Canada



### Caution

*To prevent radio interference to licensed service or co-channel Mobile Satellite systems, this device is intended to be operated indoors and away from windows to provide maximum shielding. Equipment (or its transmit antenna) that is installed outdoors is subject to licensing.*



### Caution

*Wireless devices are not user-serviceable. Do not modify them in any way. Modification to a wireless device will void the authorization to use it. Contact Gateway for service.*



### Caution

*The transmitting device embedded in this notebook may not be used with any antenna other than provide with the notebook.*



### Caution

*The 802.11A radio LAN your notebook may have been equipped with operates in the same frequency range as high power radar, which has priority use, and may damage the radio LAN if both are present and being used in the same area.*

### Industry Canada (IC) Intentional emitter per RSS 210

Low power, Radio transmitter type devices (radio frequency (RF) wireless communication devices), operating in the 2.4 GHz band and/or 5.15 – 5.35 GHz band, may be present (embedded) in your notebook system. This section is only applicable if these devices are present. Refer to the system label to verify the presence of wireless devices.

Wireless devices that may be in your system are only qualified for use in Canada if an Industry Canada ID number is on the system label.

As a general guideline, a separation of 20 cm (8 inches) between the wireless device and the body, for use of a wireless device near the body (this does not include extremities) is typical. This device should be used more than 20 cm (8 inches) from the body when wireless devices are on. The power output of the wireless device (or devices), which may be embedded in your notebook, is well below the RF exposure limits as set by Industry Canada.

Operation of this device is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of the device.

### Unintentional emitter per ICES-003

This digital apparatus does not exceed the Class B limits for radio noise emissions from digital apparatus as set out in the radio interference regulations of Industry Canada.

Le présent appareil numérique n'émet pas de bruits radioélectriques dépassant les limites applicables aux appareils numériques de Classe B prescrites dans le règlement sur le brouillage radioélectrique édicté par Industrie Canada.

### Telecommunications per Industry Canada CS-03 (for products fitted with an IC-compliant modem)

The Industry Canada label identifies certified equipment. This certification means that the equipment meets certain telecommunications network protective, operation, and safety requirements. The Department does not guarantee the equipment will operate to the users' satisfaction.

Before installing this equipment, users should make sure that it is permissible to be connected to the facilities of the local telecommunications company. The equipment must also be installed using an acceptable method of connection. In some cases, the inside wiring associated with a single-line individual service may be extended by means of a certified connector assembly. The customer should be aware that compliance with the above conditions may not prevent degradation of service in some situations.

Repairs to certified equipment should be made by an authorized Canadian maintenance facility designated by the supplier. Any repairs or alterations made by the user to this equipment, or equipment malfunctions, may give the telecommunications company cause to request the user to disconnect the equipment.

#### **Warning**

*To avoid electrical shock or equipment malfunction do not attempt to make electrical ground connections by yourself. Contact the appropriate inspection authority or an electrician, as appropriate.*

Users should make sure, for their own protection, that the electrical ground connections of the power utility, telephone lines, and internal metallic water pipe system, if present, are connected together. This precaution may be particularly important in rural areas.

The **Ringer Equivalence Number** (REN) assigned to each terminal device provides an indication of the maximum number of terminals allowed to be connected to a telephone interface. The termination on an interface may consist of any combination of devices subject only to the requirement that the sum of the Ringer Equivalence Numbers of all the devices does not exceed 5.

## Japan

本装置は、第二種情報装置（住宅地域またはその隣接した地域において使用されるべき情報装置）で住宅地域での電波障害防止を目的とした情報処理装置等電波障害自主規制協議会（VCCI）基準に適合しております。  
しかし、本装置をラジオ、テレビジョン受信機に、近接してご使用になると、受信障害の原因となることがあります。本書の説明にしたがって正しい取り扱いをしてください。

### Japanese Modem Notice

本製品を日本で使用する場合は必ず日本国モードでご使用ください。他国のモードをご使用になると電気通信事業法（技術基準）に違反する行為となります。なお、ご購入時は初期値が日本国モードとなっておりますので、そのままご利用ください。

## Laser safety statement



### Warning

*Use of controls or adjustments or performance of procedures other than those specified in this manual may result in hazardous radiation exposure. To prevent exposure to laser beams, do not try to open the enclosure of a CD or DVD drive.*

All Gateway systems equipped with CD and DVD drives comply with the appropriate safety standards, including IEC 825. The laser devices in these components are classified as “Class 1 Laser Products” under a US Department of Health and Human Services (DHHS) Radiation Performance Standard. Should the unit ever need servicing, contact an authorized service location.

## EPA ENERGY STAR



As an ENERGY STAR® Partner, Gateway has determined that this product meets the ENERGY STAR guidelines for energy efficiency when used with a computer equipped with a Display Power Management System.

## Environmental information

The product you have purchased contains extracted natural resources that have been used in the manufacturing process. This product may contain substances known to be hazardous to the environment or to human health.

To prevent releases of harmful substances into the environment and to maximize the use of our natural resources, Gateway provides the following information on how you can responsibly recycle or reuse most of the materials in your “end of life” product.

Waste Electrical and Electronic Equipment (commonly known as WEEE) should never be disposed of in the municipal waste stream (residential garbage collection). The “Crossed-Out Waste Bin” label affixed to this product is your reminder to dispose of your “end of life” product properly.



Substances such as glass, plastics, and certain chemical compounds are highly recoverable, recyclable, and reusable. You can do your part for the environment by following these simple steps:

- When your electrical or electronic equipment is no longer useful to you, “take it back” to your local or regional waste collection administration for recycling.
- In some cases, your “end of life” product may be “traded in” for credit towards the purchase of new Gateway equipment. Call Gateway to see if this program is available in your area.
- If you need further assistance in recycling, reusing, or trading in your “end of life” product, you may contact us at the Customer Care number listed in your product’s user guide and we will be glad to help you with your effort.

Finally, we suggest that you practice other environmentally friendly actions by understanding and using the energy-saving features of this product (where applicable), recycling the inner and outer packaging (including shipping containers) this product was delivered in, and by disposing of or recycling used batteries properly.

With your help, we can reduce the amount of natural resources needed to produce electrical and electronic equipment, minimize the use of landfills for the disposal of “end of life” products, and generally improve our quality of life by ensuring that potentially hazardous substances are not released into the environment and are disposed of properly.

## Notices

Copyright © 2006 Gateway, Inc.  
All Rights Reserved  
7565 Irvine Center Drive  
Irvine, CA 92618 USA

### All Rights Reserved

This publication is protected by copyright and all rights are reserved. No part of it may be reproduced or transmitted by any means or in any form, without prior consent in writing from Gateway.

The information in this manual has been carefully checked and is believed to be accurate. However, changes are made periodically. These changes are incorporated in newer publication editions. Gateway may improve and/or change products described in this publication at any time. Due to continuing system improvements, Gateway is not responsible for inaccurate information which may appear in this manual. For the latest product updates, consult the Gateway Web site at [www.gateway.com](http://www.gateway.com). In no event will Gateway be liable for direct, indirect, special, exemplary, incidental, or consequential damages resulting from any defect or omission in this manual, even if advised of the possibility of such damages.

In the interest of continued product development, Gateway reserves the right to make improvements in this manual and the products it describes at any time, without notices or obligation.

### Trademark Acknowledgments

Gateway and the Black-and-White Spot Design are trademarks or registered trademarks of Gateway, Inc. in the U.S. and other countries. SpotShop, Spotshop.com, and Your:)Ware are trademarks of Gateway, Inc. Intel, Intel Inside logo, and Pentium are registered trademarks and MMX is a trademark of Intel Corporation. Microsoft, MS, MS-DOS, and Windows are trademarks or registered trademarks of Microsoft Corporation. All other product names mentioned herein are used for identification purposes only, and may be the trademarks or registered trademarks of their respective companies.

### Macrovision statement

**If your notebook has a DVD drive and an analog TV Out port, the following paragraph applies:**

This product incorporates copyright protection technology that is protected by method claims of certain U.S. patents and other intellectual property rights owned by Macrovision Corporation and other rights owners. Use of this copyright protection technology must be authorized by Macrovision Corporation, and is intended for home and other limited viewing uses only unless otherwise authorized by Macrovision Corporation. Reverse engineering or disassembly is prohibited.



# Index

---

## A

- AC adapter
  - connecting 11
  - connector 8
- accessories
  - purchasing 29
  - safety precautions 47
- application key 17
- arrow keys 17
- audio
  - adjusting volume 21
  - back button 19
  - headphone jack 6
  - microphone jack 6
  - muting 21
  - next button 19
  - pause button 18
  - play button 18
  - stop button 19
  - volume control 6

## B

- battery
  - bay 27
  - changing 27
  - charge indicator 8
  - charging 11
  - installing 27
  - latch 9
  - locating 9
  - purchasing 29
  - recalibrating 28
  - recharging 11
  - release latch 9
  - replacing 27
- bays
  - battery 27
  - hard drive 9
  - memory 9, 32
- brightness
  - adjusting 18
  - system keys 18

## C

- cable lock 8
- cable modem 8, 13
- Caps Lock indicator 16
- cards
  - inserting memory card 25
  - inserting PC Card 26
  - memory card slot 6
  - memory cards supported 25
  - PC Card slot 7

- removing memory card 25
- removing PC Card 26
- slots 25, 26
- carrying case 29
- CD
  - inserting 24
- CD drive
  - See DVD drive
- cellular phone
  - memory cards 25
- Certificate of Authenticity 3
- clicking 21
- closing unresponsive program 15
- connecting
  - AC adapter 11
  - dial-up modem 12
  - external keyboard 17
  - keyboard 17
  - to cable modem 13
  - to DSL modem 13
  - to Ethernet 13
  - to network 13
- connections
  - audio 6
  - broadband Internet 8, 13
  - cable modem 8, 13
  - dial-up modem 7, 12
  - digital camera 7
  - digital video camera 8
  - DSL modem 8, 13
  - Ethernet 8, 13
  - external audio 6
  - external diskette drive 7
  - external speakers 6
  - Firewire 8
  - flash drive 7
  - headphone 6
  - i.Link 8
  - IEEE 1394 8
  - keyboard 7
  - microphone 6
  - modem 7, 12
  - monitor (VGA) 7
  - mouse 7
  - network 8, 13
  - power 8, 11
  - printer 7
  - scanner 7
  - speaker 6
  - USB 7
  - VGA 7
  - video camera 8
- copyright notice 54

## D

- dial-up modem 7, 12
- digital camera
  - memory card reader 6
  - USB port 7
- digital video camera
  - IEEE 1394 port 8
- directional keys 17
- display
  - switching 18
- double-clicking 21
- dragging 21
- drives
  - DVD 8, 23
  - DVD/CD-RW 8, 23
  - DVD±RW 8, 23
  - hard drive 9, 37
  - identifying drive types 23
  - multi-format DVD±RW 8, 23
  - replacing hard drive 37
  - types 23
- DSL modem 8, 13
- DVD
  - inserting 24
- DVD drive
  - identifying 23
  - installing 34
  - locating 8
  - replacing 34
  - using 23
- DVD/CD-RW drive
  - See DVD drive
- DVD±RW drive
  - See DVD drive

## E

- electrostatic discharge (ESD) 32
- Ethernet
  - connecting 13
  - jack 8, 13
- external monitor 7, 18
- EZ Pad touchpad
  - See touchpad

## F

- fan 7
- files
  - opening 21
- Firewire port 8
- Fn key 18
- folders

opening 21  
function keys 17

**G**

Gateway  
model number 2, 9  
serial number 2  
Support 3

**H**

hard drive  
bay 9  
indicator 16  
installing 37  
replacing 37  
headphone jack 6  
hot-swapping 26

**I**

i.Link port 8  
IEEE 1394 port 8  
indicators  
See status indicators  
inkjet printer 29  
installing  
battery 27  
DVD drive 34  
hard drive 37  
memory 32  
PC Card 26

**J**

jacks  
See connections

**K**

Kensington cable lock  
lock slot 8  
key combinations 18  
keyboard  
buttons 17  
connecting 17  
features 17  
locating 10  
USB port 7  
keys  
application 17  
arrow 17  
brightness 18  
directional 17  
Fn 18  
function 17  
LCD brightness 18  
LCD/CRT 18  
navigation 17  
numeric keypad 18

Pad Lock 19  
Standby 18  
system 17  
system key combinations 18  
toggle display 18  
Windows 18

**L**

labels  
Microsoft Certificate of  
Authenticity 3  
model number 2, 9  
serial number 2  
laser printer 29  
latch  
battery 9  
LCD panel release 6  
LCD panel  
release latch 6  
switching display 18  
LCD/CRT system key 18  
lock  
Kensington cable 8

**M**

memory  
bay 9  
installing 32  
purchasing 29  
removing 32  
replacing 32  
memory card reader  
locating 6  
memory cards supported 25  
using 25  
microphone jack 6  
Microsoft Certificate of  
Authenticity 3  
model number 2  
modem  
cable 8, 13  
connecting 12, 13  
dial-up 7, 12  
DSL 8, 13  
jack 7, 12  
monitor  
port 7  
using 18  
mouse  
USB port 7  
See also touchpad  
moving  
pointer 20  
screen objects 21  
MP3 player  
memory cards 25

multimedia  
adjusting volume 6, 21  
using DVD drive 23  
muting sound 6, 21

**N**

navigation keys 17  
network jack 8, 13  
networking  
turning off wireless network 22  
turning on wireless network 22  
Num Lock  
status indicator 16, 19  
system key 19  
numeric keypad  
status indicator 16  
using 18

**O**

opening  
files 21  
folders 21  
LCD panel 6  
notebook 6  
programs 21  
shortcut menu 21

**P**

PC Card  
adding 26  
eject button 26  
inserting 26  
installing 26  
removing 26  
slot 26  
PCMCIA card  
See PC Card  
PDA  
memory cards 25  
pointer  
identifying 20  
moving 20  
power  
AC adapter 11  
battery 27, 28  
button 10, 18  
connector 8, 11  
indicator 8, 14  
source problems 12  
Standby mode 14, 18  
status indicator 8  
turning off notebook 14  
turning on notebook 14  
printer  
inkjet 29  
laser 29

- USB port 7
- programs
  - closing unresponsive 15
  - opening 21
- projector
  - using 18
- R**
- RAM
  - See memory
- rebooting notebook 15
- recalibrating battery 28
- replacing
  - See installing
- resetting notebook 15
- restarting notebook 15
- right-clicking 21
- rocker switch 20
- S**
- safety
  - general precautions 46
  - static electricity 32
- scanner
  - USB port 7
- screen objects
  - getting information 21
  - moving 21
  - selecting 21
- security features
  - Kensington cable lock 8
- serial number 2
- setting up
  - safety precautions 46
- shortcut menus
  - accessing 21
- shortcuts
  - opening menu 21
- shutting down notebook 14, 15
- SO-DIMM
  - See memory
- sound
  - adjusting 21
  - controls 21
  - muting 21
- speakers
  - jack 6
- Standby
  - mode 14, 18
  - system key 18
- starting
  - notebook 14
  - programs 21
- static electricity 32

- status indicators
  - battery charge 8
  - Caps Lock 16
  - drive activity 16
  - hard drive 16
  - location 10
  - Num Lock 19
  - numeric keypad 16, 19
  - Pad Lock 16
  - power 8
  - toggle on or off 18
- surge protector 12
- Suspend 18
- system identification label 2, 9
- system keys
  - combinations 18
  - locating 17

**T**

- technical support
  - Support 3
- touchpad
  - buttons 20
  - clicking 21
  - double-clicking 21
  - dragging screen objects 21
  - locating 10
  - moving pointer 20
  - moving screen objects 21
  - opening files, folders, and programs 21
  - opening shortcut menu 21
  - right-clicking 21
  - rocker switch 20
  - selecting screen objects 21
- turning off
  - notebook 14, 15
  - wireless network 18, 22
- turning on
  - notebook 14
  - wireless network 18, 22

**U**

- upgrading 31
- USB port 7

**V**

- VGA port 7
- video
  - monitor port 7
  - VGA port 7
- volume
  - adjusting 6, 21
  - controls 6, 21
  - muting 6, 21

**W**

- waking up notebook 14
- Windows
  - key 18
  - Product Key Code 3
- wireless network
  - button 18
  - turning off 22
  - turning on 22





MAN MAGIC LC HW REF R0 11/05



8511189